



Installation Guide

Included Installation Instructions

Network Camera For professional use only

Model No. **WV-U2542LA** Outdoor use

WV-U2532LA Outdoor use



WV-U2542LA

About the user manuals

- Product documentation is composed of the following documents.
- Installation Guide (this document):** Provides information about "Precautions", "Precautions for installation" and the installation method.
- Basic Information (in the following manual website):** Provides information about "Precautions for use" and "Detail specifications".
- Operating Instructions (in the following manual website):** Explains how to perform the settings and how to operate this camera. https://r-pro.com/global/en/surveillance/documentation_database



*-Control No.: C****- used in these documents should be used to search for information on our support website (https://r-pro.com/global/en/surveillance/training_support/support/technical_information) and will guide you to the right information.

- Before attempting to connect or operate this product, please read these instructions carefully and save this manual for future use.
- microSDXC/ microSDHC/ microSD memory card is described as microSD memory card. Its external appearance and other parts shown in this manual may differ from the actual product within the scope that will not interfere with normal use due to improvement of the product.

For U.S. and Canada:

i-PRO Americas Inc.
<https://www.i-pro.com/>

For Europe and other countries:

i-PRO Co., Ltd. Fukuoka, Japan
<https://www.i-pro.com/>
i-PRO EMEA B.V, UK Branch
1010 Cambourne Business Park,
Cambridgehire CB23 6DP
UK
CE
Authorized Representative in EU:
i-PRO EMEA B.V.
Laarderhoogtweg 25, 1101 EB
Amsterdam, Netherlands



© i-PRO Co., Ltd, 2022 No3021-1042
Printed in China

Disposal of Old Equipment and Batteries
Only for European Union and countries with recycling systems

These symbols on the products, packaging, and/or accompanying documents mean that used electrical and electronic products and batteries must not be mixed with general household waste. For proper treatment, recovery and recycling of old products and used batteries, please take them to applicable collection points in accordance with your national legislation. By disposing of them correctly, you will help to save valuable resources and prevent any potential negative effects on human health and the environment. For more information about collection and recycling, please contact your local authority. Penalties may be applicable for incorrect disposal of this waste, in accordance with national legislation.

Note for the battery symbol (bottom symbol)
This symbol might be used in combination with a chemical symbol. In this case it complies with the requirement set by the Directive for the chemical involved.

FOR U.S.A.

Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

FCC CAUTION: Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Supplier's Declaration of conformity
Trade name : i-PRO
Model No. : WV-U2542LA
WV-U2532LA
Responsible Party :
i-PRO Americas Inc,
8550 Fallbrook Drive, Suite 200 Houston,
Texas 77064
Support Contact : 1-800-513-5417



For U.S.A.

The model number and serial number of this product may be found on the surface of the unit. You should note the model number and serial number of this unit in the space provided and retain this book as a permanent record of your purchase to aid identification in the event of theft.
Model No. _____
Serial No. _____

For U.S.A.

This device complies with part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

For Canada
CAN ICES-3(A)/NMB-3(A)

Méthode d'installation	Vis de fixation recommandée	La capacité de traction minimale requise
Montez directement la caméra sur la surface d'installation à l'aide de la plaque de fixation. Montez la caméra sur la surface d'installation à l'aide du support de base.	M4 × 16 mm (5/8 pouces) 7/4 dt.	196 N (44 lbf)

* La longueur de la vis est un exemple lors de l'installation de la caméra au plafond ou sur un mur robuste d'une épaisseur de 20 mm (25/32 pouces) ou plus.

- Caution:**
- The network camera is only intended for a connection to an ethernet or PoE network without routing to the outside plant.
 - This product has no power switch. Be sure to install disconnect devices such as a circuit breaker to shut down the main power of power supplying equipment to this product.
 - Before attempting to connect or operate this product, please read these instructions carefully.
- Notice:**
- This product is not suitable for use in locations where children are likely to be present.
 - Do not install this product in locations where ordinary persons can easily reach.
 - This product is a professional equipment.
 - For information about screws and other parts required for installation, refer to the corresponding section of this document.
- Direct current symbol

Precautions

- Do not insert any foreign objects.**
Fire or electrical shock may be caused if water or any foreign objects, such as metal objects, enter inside the unit. Turn the power off immediately and contact qualified service personnel for service.
- Do not use this product in an inflammable atmosphere.**
Failure to observe this may cause an explosion resulting in injury.
- Avoid installing this product in the locations where salt damage occurs or corrosive gas is produced.**
Otherwise, the mounting portions will deteriorate and injury or accidents due to a fall of the product may occur.
- Do not strike or give a strong shock to this product.**
Failure to observe this may cause injury or fire.
- Keep microSD memory cards away from infants and children.**
Otherwise, they may swallow the cards by mistake.
- Do not hang down from this product or use this product as a pedestal.**
Failure to observe this may cause injury or accidents.
- Do not install this product on a place that is greatly influenced by wind.**
Installation on a place where the wind speed is 60 m/s (approx. 134 mph) or more may cause a fall of the product resulting in injury or accidents.
- Do not sprinkle more water, exceeding the performance limit of waterproof with a high pressure cleaning machine, etc.**
Fire or electrical shock may be caused by immersion.
- Do not attempt to disassemble or modify this product.**
Failure to observe this may cause fire or electric shock. Consult the dealer for the repair or inspections.
- Do not install or clean the camera, or touch this product, the power cable or the connected cables during thunder storms.**
Failure to observe this may cause electric shock.
- Refer installation work to the dealer.**
Installation work requires technique and experience. Failure to observe this may cause fire, electric shock, injury, or damage to the product. Be sure to consult the dealer.
- Stop the operation immediately when something is wrong with this product.**
When smoke goes up from the product, the smell of smoke comes from the product, or the exterior of the product has deteriorated, continued use will cause a fire or fall of the product resulting in injury, or damage to the product. In this case, turn the power off immediately and contact qualified service personnel for service.
- Select an installation area that can support the total weight.**
Selecting an inappropriate installation surface may cause the product to fall down or topple over, resulting in injury or accidents. Installation work shall be started after sufficient reinforcement.
- Periodic inspections shall be conducted.**
Rust on the metal parts or screws may cause a fall of the product resulting in injury or accidents. Consult the dealer for the inspections.
- The exclusively designed mount bracket shall be used.**
Failure to observe this may cause a drop resulting in injury or accidents.

- Use the exclusively designed mount bracket for installation.
- The screws and bolts must be tightened to the specified torque.**
Failure to observe this may cause a drop resulting in injury or accidents.
 - Turn the power off when do wiring of this product.**
Failure to observe this may cause electric shock. In addition, short circuit or wrong wiring may cause fire.
 - Install this product in a location high enough to avoid people and objects from bumping the product.**
Failure to observe this may cause injury.
 - Do not install this product in locations subject to vibration.**
Loosening of mounting screws or bolts may cause a fall of the product resulting in injury or accidents.
 - Correctly perform all wiring.**
Short circuits in the wiring or incorrect wiring may cause fire or electrical shock.
 - Install the product securely on a wall or a ceiling in accordance with the installation instructions.**
Failure to observe this may cause injury or accidents.
 - Do not rub the edges of metal parts with your hand.**
Failure to observe this may cause injury.
 - Do not touch the metal part of the bottom side of the product.**
The metal part of the bottom side may become hot while the product is in use. Direct skin contact with high-temperature parts of the product may cause burns.
 - Turn the power off when cleaning this product.**
Failure to observe this may cause injury.

About notations

The following notations are used when describing the functions limited for specified models. The functions without the notations are supported by all models.

U2542 The functions with this notation are available when using the model WV-U2542LA (4M pixel model).

U2532 The functions with this notation are available when using the model WV-U2532LA (Full HD model).

Open Source Software

- This product contains open source software licensed under GPL (GNU General Public License), LGPL (GNU Lesser General Public License), etc.
- Customers can duplicate, distribute and modify the source code of the software under license of GPL and/or LGPL. For details concerning licensing and source code of open source software, click "Click here for OSS information" on "Support" page of the setup menu of this product and read the displayed content.
- Please note that we shall not respond to any inquiries regarding the contents of the source code.

Copyright

Except for open source software licensed under GPL/LGPL, and so on, distributing, copying, disseminating, reverse compiling and reverse engineering of the software provided with this product are all expressly prohibited. In addition, exporting any software provided with this product violating export laws is prohibited.

Trademarks and registered trademarks

- Microsoft, Windows, Windows Media, Internet Explorer, Microsoft Edge, and ActiveX are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.
- Intel and Intel Core are trademarks of Intel Corporation or its subsidiaries in the U.S. and/or other countries.
- Adobe, Acrobat, and Reader are either registered trademarks or trademarks of Adobe in the United States and/or other countries.
- microSDXC Logo is a trademark of SD-3C, LLC.
- iPad and iPhone are trademarks of Apple Inc., registered in the U.S. and other countries.
- Android and Google Chrome are trademarks of Google LLC.
- Firefox is a trademark of the Mozilla Foundation in the US and other countries.
- The word "QR Code" is a registered trademark of DENSO WAVE INCORPORATED in Japan and other countries.
- All other trademarks identified herein are the property of their respective owners.

Precautions for installation

- i-PRO Co., Ltd. assumes no responsibility for injuries or property damage resulting from failures arising out of improper installation or operation inconsistent with this documentation.**
- In order to prevent injury, the product must be securely mounted to a wall or ceiling according to Installation Guide.**
- Installation area for this product**
Select an appropriate place for the installation area (such as a strong wall or ceiling) in your particular environment,
 - Make sure that the installation area is strong enough to hold this product, such as a concrete ceiling.
 - Install the camera in the foundation area of the architecture or where sufficient strength is assured.
 - Do not mount the product on a plaster board or a wooden section because they are too weak. If the product is unavoidably mounted on such a section, the section shall be sufficiently reinforced.
- Install the product in areas that do not receive direct sunlight.**
When the product is installed outside in areas that receive direct sunlight, such as on external walls, use the optional "Sun Shade WV-QSR500-W or WV-QT118".
- Do not place this product in the following places**
 - Locations where a chemical agent is used such as a swimming pool
 - Locations subject to moisture or oil smoke such as a kitchen
 - Locations that have a specific environment that is subject to an inflammable atmosphere or solvents
 - Locations where a radiation, an X-ray, a strong radio wave or a strong magnetic field is generated
 - Locations near coasts directly exposed to sea breezes, or locations subject to corrosive gases such as from hot springs, volcanic regions, etc.
 - Locations where the temperature is not within the specified range

- Locations subject to vibrations, such as on vehicles, marine vessels, or above product lines (This product is not designed for on-vehicle use).
- Locations subject to condensation as the result of severe changes in temperature
- Locations near rubber products (packing, rubber feet, etc.)
- Screw tightening**
Do not use an impact driver. Use of an impact driver may damage the screws or cause tightening excessively.
- About reflection of light from outside or IR light**
A glow may appear on the screen depending on the incident angle of external light. In the case of using the IR light, installation of a camera near a wall may cause reflection of infrared rays resulting in a part of the screen or the entire screen turning whitish.
 - Refer to our support website <Control No.: C0109> for image examples and measures to take.
- Take notice of humidity**
Install this product when the humidity is low. If installation is performed when it is raining or in very humid conditions, the inside may be affected by humidity, causing mist-over inside the dome cover.
- Protection from lightning**
When cables are used outdoors, there is a chance that they may be affected by lightning. In such a case, install a lightning arrestor close to the camera, and make the length of the network cable between the camera and lightning arrestor as short as possible to prevent the camera from being affected by lightning.
- When noise disturbance may happen**
Noise may appear in video or audio near a strong electric field from a TV or radio antenna, motors and transformers, or a strong electric field/magnetic field from a power line (lamp line) of AC100 V or more. Conduct the power distribution work to keep 1 m (32.8 feet) away from them or conduct the electric conduit work using metal pipes. (Be sure to make ground connection of the metal pipes).
- Make sure to remove this product if it will no longer be used.**
- This product has no power switch.**
When turning off the power, disconnect the power supply from the PoE device.
- About the battery**
A battery is installed inside the camera. Do not leave the battery exposed in environments of excessive heat as a result of sunlight or fire.

Equipment classification and power source indication label

Refer to the indication label on the bottom side of this unit for the equipment classification, power source, and other information.

Installation method	Recommended screw ¹	Minimum pull-out strength ²
Directly mount : Directly mount the camera onto the ceiling or wall.	M4 × 16 mm (5/8 inches) ³ / 4pcs. M4 × 16 mm (5/8 inches) ³ / 2pcs ⁴ .	196 N (44 lbf)
Gangbox/ Junction box : Mount the camera to a gangbox/ junction box.	M4 × 16 mm (5/8 inches) ³ / 4pcs.	196 N (44 lbf)
Base bracket : Mount the camera using the WV-QJB501-W or WV-Q193.	M4 × 16 mm (5/8 inches) ³ / 4pcs. ⁵	196 N (44 lbf)

Mount the camera using the exclusively designed mount bracket (See "Optional accessories"). Refer to the operating instructions of each bracket.

Troubleshooting

Before requesting service, refer to "Troubleshooting" of Basic Information and Operating Instructions. Then, confirm the trouble.

Specifications *For further information, refer to the Basic Information.

Power source ¹⁾ :	PoE (IEEE802.3af compliant)
Power consumption ²⁾ :	PoE DC 48 V : 150 mA/ Approx. 7.2 W (Class 0 device) U2542 PoE DC 48 V : 140 mA/ Approx. 6.7 W (Class 0 device) U2532
Operating environment	
Ambient operating temperature:	-30 °C to +50 °C [-22 °F to +122 °F] (Power On range: -20 °C to +50 °C [-4 °F to +122 °F])
Ambient operating humidity:	10 % to 100 % (no condensation)
Storage environment	
Storage temperature:	-30 °C to +60 °C [-22 °F to +140 °F]
Storage humidity:	10 % to 95 % (no condensation)
Waterproof ³⁾ :	IP66 (IEC 60529), Type 4X (UL50E) NEMA 4X compliant
Shock resistance:	IK10 (IEC 62262)
Wind resistance:	Up to 40 m/s (approx. 89 mph)
Dimensions:	ø154 mm × 103 mm × 103 mm [ø6.1/ø6.16 inches × 4.1/4.16 inches (H)] Dome radius 42 mm [1.21/32 inches]
Mass:	Approx. 1.0 kg (2.21 lbs)
Finish:	Main body : Aluminum die cast/ PC resin, i-PRO white Outer fixing screws : Stainless steel (Corrosion-resistant treatment) Dome cover : Polycarbonate resin, Clear
Others:	Tamper-resistant enclosure ⁴⁾

- *1 Refer to our support website <Control No.: C0106> for further information about Power source and Power consumption information.
- *2 Only when installation work is properly performed according to the Installation Guide and appropriate waterproof treatment is performed.
- *3 Component that has a structure on which the screws that are accessible after installation cannot be screwed or unscrewed using an ordinary screwdriver.

Optional accessories¹⁾

Ceiling mount (Smoke type):	WV-Q105A ²⁾	Dome cover: WV-CW7SN (Smoke type with ClearSight coating)
Dome cover (Smoke type):	WV-CW7S ²⁾	Dome cover: WV-CW7CN (Clear type with ClearSight coating)
Sun shade ⁴⁾ :	<i-PRO white brackets> ³⁾ WV-QSR500-W WV-Q7118	<Light gray brackets> ³⁾ - -
Base bracket:	WV-QJB501-W WV-Q193	<Fine silver brackets> ³⁾ - -
Ceiling mount bracket:	WV-QEM500-W	WV-Q169A
Ceiling mount bracket:	WV-QCL501-W	WV-Q178 WV-Q121B
Wall mount bracket:	WV-QWL501-W	WV-Q185 WV-Q122A
Mount bracket:	WV-QRS501-W	WV-Q186 WV-Q124
Pole mount bracket:	WV-QPL500-W	WV-Q182 WV-Q188
Corner mount bracket:	WV-QCN500-W	WV-Q183 WV-Q189
Attachment Pipe Bracket:	WV-QAT500-W	WV-Q179 WV-Q123A

- *1 Refer to our support website <Control No.: C0501> for further information about optional accessories.
- *2 This product can only be installed indoors when WV-Q105A is used to install it on the ceiling.
- *3 Refer to our support website <Control No.: C0112> for further information about combinations of each bracket.
- *4 When using Sun shade (WV-QSR500-W or WV-Q7118), Base bracket (WV-QJB501-W or WV-Q193) is required.

Standard accessories

Installation Guide (this document), 1 pc. Code label¹⁾, 1 pc.
IMPORTANT SAFETY INSTRUCTIONS, 1 pc.

- *1 This label may be required for network management. Use caution not to lose this label.
- The following parts are used during installation procedures.**
- Attachment plate, 1 pc. RJ45 waterproof connector cover, 1 pc.
- Fixing screws for attachment plate, 5 pcs. RJ45 waterproof connector cap, 1 pc.
- (M4 × 8 mm (5/16 inches)), (of them, 1 for spare) Bit (hex wrench) screw size 6.35 mm (1/4 inches) T20, 1 pc.
- Template, 1 sheet Attachment for the conduit, 1 pc.
- Cable cover²⁾, 1 pc. PAN table fixing screw, 1 pc.
- *2 The cable cover is attached to the camera.

Other items that are needed (not included)

Installation method	Recommended screw ¹	Minimum pull-out strength ²
Directly mount : Directly mount the camera onto the ceiling or wall.	M4 × 16 mm (5/8 inches) ³ / 4pcs. M4 × 16 mm (5/8 inches) ³ / 2pcs ⁴ .	196 N (44 lbf)
Gangbox/ Junction box : Mount the camera to a gangbox/ junction box.	M4 × 16 mm (5/8 inches) ³ / 4pcs.	196 N (44 lbf)
Base bracket : Mount the camera using the WV-QJB501-W or WV-Q193.	M4 × 16 mm (5/8 inches) ³ / 4pcs. ⁵	196 N (44 lbf)

Mount the camera using the exclusively designed mount bracket. Refer to the operating instructions of each bracket.

- *1 Select screws according to the material of the location that the camera will be mounted to. In this case, wood screws and nails should not be used.
- *2 For information about the minimum pull-out strength, refer to our support website <Control No.: C0120>.
- *3 The screw length is an example when installing the camera on a robust installation surface with a thickness of 20 mm (25/32 inches) or more.
- *4 When using the attachment for the conduit.
- *5 2 pcs. when mounting WV-QJB501-W or WV-Q193 to a single-gang gangbox/ junction box

- RJ45 plug, Ethernet cable (category 5e or better, straight, all 4 pairs (8 pins))
- Tools

